

## [ Quick Program guide ]

---

**email:** [be.seen@hotmail.com](mailto:be.seen@hotmail.com)

**skype:** pablochen.1996

**We bring value to a lot projects during the past 20 years, also save a lot cost for many customers.**

**If any problem, please don't return directly, that will bring big loss to me. I do support with my heart, Contact me for solution.**

**Any question is good question, we have over 20 years experience, Our support is for ever.**

**CREATE SECURITY FOR YOU**

## Contents

1. Quick Trial .....	2
1.1 Quick try: Enroll Card or Key Fob.....	2
1.2 Quick Try: Enroll PIN Code/Password. ....	2
2. Official Do program for all users.....	3
2.1 Want to delete all users and start from Fresh.....	3
2.2 About user ID Number .....	3
2.3 How to Add Card/Fob User <i>with User ID Number</i> .....	4
2.4 How to delete Card/Fob User <i>by User ID Number</i> .....	4
2.5 How to Enroll or Delete PIN/Password Code.....	5
3. Want to change the default program code .....	5

## 1. Quick Trial

After wire and power on the system (**we have detail wire diagram and video for how to wire**), Now we can do a **quick trial**.

### 1.1 Quick try: Enroll Card or Key Fob

Press: \* **999999** #

Press: **1**

Please swipe a card or Fob, can swipe continuously for different card/fobs

press \* \* to quit programming mode

**Now swipe this card or Key Fob, can open lock, also the LED of Keypad become to Blue for a few seconds.**

### 1.2 Quick Try: Enroll PIN Code/Password.

For example, Person: John, user ID number: 120, Password: 3458 to open door

To program John, steps as below:

Press: \* **999999** #

Press: **1**

press 120 # ( **120** here is user ID number)

Press **3458** #

press \* \* to quit

**Now press 3458 # , can open lock.**

## 2. Official Do program for all users

### 2.1 Want to delete all users and start from Fresh

Previously, maybe do some trial, now do official program, suggest that remove all users and begin from fresh stage, **the steps** are:

Press: \* 999999 # ( enter programming mode )  
press 2 (to delete user)  
press 0 0 0 0#  
press \* \* to quit

**Now all enrolled users( card or keyfob or pin code, all deleted)**

### 2.2 About user ID Number

**Kindly Notes: Possibly a person will not work for you in future, you need to delete his/her open privilege. When do the enroll programming, we suggest you assign unique user ID number for each user and save these information, it will be easy to delete user in the future. For example, the format can be:**

John( user ID Number: 1)  
Peter(user ID Number: 2)  
...  
Chris(User ID number:98)  
...  
Mary(user ID Number: 101)

## 2.3 How to Add Card/Fob User *with User ID Number*

Person: Mary, Assign user ID number: 101 to her

To program Mary's card or Key Fob, steps as below:

Press: \* 999999 #

press 1 (to add user)

press 101 # ( 101 here is user ID Number)

Press swipe the card or Fob

Press #

press \* \* to quit programming mode

**Now swipe this card or Key Fob, can open lock.**

## 2.4 How to **delete** Card/Fob User *by User ID Number*

Remove this person

Person: Mary, user ID: 101, if **have no** Mary's card or fob on hand, follow below steps:

Press: \*999999# ( enter programming mode )

press 2 (to delete user)

press 101# ( **101 here is user ID number, so need to record some where when you enroll the user, so that you know which user ID belongs to whom** )

Then press \* \* to quit

with above steps, the user( which user ID=101) will be deleted.

If have the card or fob on hand, it's easier, no need the user ID, steps:

Press: \*999999# ( enter programming mode )

press 2 (to delete user)

Swipe Mary's card or Fob

Press #

press \* \* to quit

with above steps, the use-Mary will be deleted.

## 2.5 How to Enroll or Delete PIN/Password Code

Add Person: Chris, Assign user ID Number: 98, Password: 1688 to open door

Press: \* **999999** #

Press: **1**

press 98 # ( **98** here is user ID number)

Press **1688** #

press \* \* to quit

**Now press 1688 # , can open lock.**

If some day in future, need to remove Chris's open privilege:

Press: \*999999# ( enter programming mode )

press 2 (to delete user)

press 98# ( **98 here is user ID Number** )

press \* \* to quit

with above steps, the user Chris( which user ID=98) will be deleted.

## 3. Want to change the default program code

Firstly, enter programming mode by: \* Master code #, 999999 is the default master code

then press: 0 new code # new code #

for example, new code is: 987654, you should: 0 987654 # 987654 #