

[Quick Program guide]

email: be.seen@hotmail.com

skype: [pablochen.1996](#)

Thank you very much for placing an order. If you have any questions or concerns, **please refrain from returning our products directly, as it would result in significant losses for us.**

We take pride in delivering high-quality products and excellent service support. **By giving us the opportunity to assist you, we can add substantial value** to your project and help you save significantly.

CREATE SECURITY FOR YOU

Contents

1. Quick Trial	2
1.1 Quick Try: Enroll PIN Code/Password.	2
2. Official Do program for all users	2
2.1 Want to delete all users and start from Fresh.....	2
2.2 About user ID Number(4-digits)	2
2.3 How to Delete PIN/Password Code	3
3. Want to change the default program code	3

1. Quick Trial

After wire and power on the system (**we have detail wire diagram and video for how to wire**), Now we can do a **quick trial**.

1.1 Quick Try: Enroll PIN Code/Password.

For example, Person: John, user ID number: **35**, Password: **3458** to open door

To program John, steps as below:

Press: **# 123456 #** -- this is to enter program mode

Press: **23** -- this is to add pin code user

Then press: 0035 3458 #

(0035 here is user ID number-4 digits, 3458 here is pin code)

Now program done.

Now press **3458 #** , can open lock.

2. Official Do program for all users

2.1 Want to delete all users and start from Fresh

Previously, maybe do some trial, now do official program, suggest that remove all users and begin from fresh stage, **the steps** are:

Press: # 123456 # (enter programming mode)

press 40 0 0 0 0 #

Now all enrolled users deleted

2.2 About user ID Number(4-digits)

Kindly Notes: Possibly a person will not work for you in future, you need to delete his/her open privilege. When do the enroll programming, we suggest you assign

unique user ID number for each user and save these information, it will be easy to delete user in the future. For example, the format can be:

John(user ID Number: 0001)

Peter(user ID Number: 0002)

...

Chris(User ID number:0098)

...

Mary(user ID Number: 0101)

2.3 How to Delete PIN/Password Code

For example, have user: Chris, Assigned user ID Number: 0098,

If some day in future, need to remove Chris's open privilege:

Press: # 123456 # (enter programming mode)

press 42 (to delete user)

press 0098# (**0098 here is user ID Number**)

with above steps, the user Chris(which user ID=0098) will be deleted.

3. Want to change the default program code

Firstly, enter programming mode by: # Master code #, 123456 is the default master code

then press: 0 new code # new code #

for example, new code is: 987654, you should: 0 987654 # 987654 #

If forget the program Master code, follow below to reset:

<https://vimeo.com/927014349/0a9866718b>